

COLOUR FILTERS

019	Fire	106	Primary Red *	135	Deep Golden Amber	161	Slate Blue
026	Bright Red	107	Light Rose	136	Pale Lavender *	164	Flame Red
027	Medium Red	109	Middle Rose	137	Special Lavender	170	Deep Lavender
061	Mist Blue	111	Dark Pink	138	Pale Green	180	Dark Lavender *
068	Sky Blue	115	Peacock Blue	139	Primary Green	181	Congo Blue *
071	Tokyo Blue	116	Medium Blue-Green	140	Summer Blue	195	Zenith Blue *
075	Evening Blue	118	Light Blue	141	Bright Blue	196	True Blue
079	Just Blue	119	Dark Blue	142	Pale Violet	197	Alice Blue
085	Deeper Blue	120	Deep Blue	147	Apricot *	200	Double CT Blue *
101	Yellow	122	Fern Green	151	Gold Tint **	201	Full CT Blue **
102	Light Amber	124	Dark Green	152	Pale Gold **	202	Half CT Blue
103	Straw	126	Mauve	153	Pale Salmon *	343	Special Medium Lavender
104	Deep Amber	128	Bright Pink	156	Chocolat	700	Perfect Lavender
105	Orange *	132	Medium Blue	158	Deep Orange		

All filters are available for Par 64.

* → Also available for fresnel.

** → Also available for fresnel AND profile.

FIXTURES

Stage

Par 64 72x DTS Par 64 CP62
 Par 64 8x DTS Par 64 CP62 (Floor)
 ACL 3x DTS ACL-set (8x 28V-250W)
 Blinders 4x DTS Fourlight Par 36 DWE
 Front 12x ADB FRESNEL - 800 W
 12x Selcon SPX Zoom - 800 W (15 - 35 degrees)

Spots 12x Robe Robin 600E Spot
 Washes 12x Robe Robin 600E wash
 Strobes 7x Martin Atomic 3000 (5x above stage, 2x available as floorset)

Hall

Ledwashes 6x Robe Robin 300 Ledwash
 Ledpars 20x Robe Ledforce 18
 40x Lightmaxx NanoPar

On request

Beams 8x Clay Paky Sharpy
 Sunstrips 8x Showtec Active Sunstrip
 Ledwashes 6x Robe Robin 300 Ledwash

ATMOSPHERE

Haze 2x Swefog XEON II Intellahazer
 Smoke 2x MagicFX SmokeJet (**On request**)

CONTROL

Dimmers 3x ADB Eurorack (24 channels 2,3KW)
 1x DIG12 mobile rack (12 channels 2,3KW)
 Desk 1x MA Lighting GrandMA Light with GrandMA2 fader wing
 Focushand 1x ELC Focushand 3
 Patch 6x DMX 5p (2x free at stage right)
 3x Ethercon Cat 6 (FOH, backstage, stage left & right)

FREE POWER SUPPLY

Light Mainstage 1x 400V/63A/3P

Mainstage: UNIVERSE 1 (Stage)

Fixture Type	Brand		Mode	Channels	Address	Location
Par 64	DTS	1KW MFL	-	12	1-12	LX 3
Par 64	DTS	1KW MFL	-	12	13-24	LX 2
Par 64	DTS	1KW MFL	-	12	25-36	LX 1
ACL	DTS	8x 250W ACL	-	1	37-39	LX1- LX3
Blinder	DTS	Fourlight Par 36 DWE (2ch)	-	8	40-47	LX 1
Fresnel	ADB	F101 (13-59o) 1KW	-	6	48-53	Front
Fresnel	ADB	F101 (13-59o) 1KW	-	6	54-59	Hall
Profile	Selecon	SPX Zoom (15-35o) - 800W	-	6	60-65	Front
Profile	Selecon	SPX Zoom (15-35o) - 800W	-	6	66-71	Hall
↓ 12x ↓						
Spot	Robe	Robin 600 ^E Spot	1	32	73	LX 3
Spot	Robe	Robin 600 ^E Spot	1	32	105	LX 3
Spot	Robe	Robin 600 ^E Spot	1	32	137	LX 3
Spot	Robe	Robin 600 ^E Spot	1	32	169	LX 3
Spot	Robe	Robin 600 ^E Spot	1	32	201	LX 2
Spot	Robe	Robin 600 ^E Spot	1	32	233	LX 2
Spot	Robe	Robin 600 ^E Spot	1	32	265	LX 2
Spot	Robe	Robin 600 ^E Spot	1	32	297	LX 2
Spot	Robe	Robin 600 ^E Spot	1	32	329	LX 1
Spot	Robe	Robin 600 ^E Spot	1	32	361	LX 1
Spot	Robe	Robin 600 ^E Spot	1	32	393	LX 1
Spot	Robe	Robin 600 ^E Spot	1	32	425	LX 1
↓ 5x ↓						
Strobe	Martin	Atomic	Effects (4CH)	4	457	LX 3
Strobe	Marti	Atomic	Effects (4CH)	4	461	LX 3
Strobe	Martin	Atomic	Effects (4CH)	4	465	LX 2
Strobe	Martin	Atomic	Effects (4CH)	4	469	LX 2
Strobe	Martin	Atomic	Effects (4CH)	4	473	LX 1

Mainstage: UNIVERSE 2

Fixture Type	Brand		Mode	Channels	Address	Location
↓ 8x ↓						
Ledpar	LightMaxx	Nano Par	-	8 CH	1	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	9	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	17	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	25	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	33	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	41	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	49	In carre truss
Ledpar	LightMaxx	Nano Par	-	8 CH	57	In carre truss
↓ 12x ↓						
Wash	Robe	Robin 600 ^E Wash	1	19	65	LX 3
Wash	Robe	Robin 600 ^E Wash	1	19	84	LX 3
Wash	Robe	Robin 600 ^E Wash	1	19	103	LX 3
Wash	Robe	Robin 600 ^E Wash	1	19	122	LX 3
Wash	Robe	Robin 600 ^E Wash	1	19	141	LX 2
Wash	Robe	Robin 600 ^E Wash	1	19	160	LX 2
Wash	Robe	Robin 600 ^E Wash	1	19	179	LX 2
Wash	Robe	Robin 600 ^E Wash	1	19	198	LX 2
Wash	Robe	Robin 600 ^E Wash	1	19	217	LX 1
Wash	Robe	Robin 600 ^E Wash	1	19	236	LX 1
Wash	Robe	Robin 600 ^E Wash	1	19	255	LX 1
Wash	Robe	Robin 600 ^E Wash	1	19	274	LX 1
↓ 6x ↓						
Ledwash	Robe	Robin 300 Ledwash	2	21	293	Hall
Ledwash	Robe	Robin 300 Ledwash	2	21	314	Hall
Ledwash	Robe	Robin 300 Ledwash	2	21	335	Hall
Ledwash	Robe	Robin 300 Ledwash	2	21	356	Hall
Ledwash	Robe	Robin 300 Ledwash	2	21	377	Hall
Ledwash	Robe	Robin 300 Ledwash	2	21	398	Hall
↓ 14x ↓						
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	419	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	425	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	431	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	437	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	443	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	449	Balcony
↓ 2x ↓						
Spot	Showtec	Phantom 50	13 Ch	13	455	Hall
Spot	Showtec	Phantom 50	13 Ch	13	468	Hall

Mainstage: UNIVERSE 3

Fixture Type	Brand		Mode	Channels	Address	Location
		↓ 30x ↓				
Ledpar	Lightmaxx	Nanopar	-	8	1 – 233	Under balcony
		↓ 14x ↓				
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	241	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	247	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	253	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	259	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	265	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	271	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	277	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	283	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	289	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	295	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	301	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	307	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	313	Balcony
Ledpar	Robe	Ledforce 18 RGBW	6 CH	6	319	Balcony

Mainstage: UNIVERSE 4 (On request)

Fixture Type	Brand		Mode	Channels		Location
		↓ 8x ↓				
Beam	Clay paky	Sharpy	Vector	20	1	Floor
Beam	Clay paky	Sharpy	Vector	20	21	Floor
Beam	Clay paky	Sharpy	Vector	20	41	Floor
Beam	Clay paky	Sharpy	Vector	20	61	Floor
Beam	Clay paky	Sharpy	Vector	20	81	Floor
Beam	Clay paky	Sharpy	Vector	20	101	Floor
Beam	Clay paky	Sharpy	Vector	20	121	Floor
Beam	Clay paky	Sharpy	Vector	20	141	Floor
		↓ 8x ↓				
Sunstrip	Showtec	Active Sunstrip	10CH	10	161	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	171	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	181	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	191	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	201	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	211	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	221	Floor
Sunstrip	Showtec	Active Sunstrip	10CH	10	231	Floor
		↓ 6x ↓				
Ledwash	Robe	Robin 300 Ledwash	2	21	241	Floor
Ledwash	Robe	Robin 300 Ledwash	2	21	262	Floor
Ledwash	Robe	Robin 300 Ledwash	2	21	283	Floor
Ledwash	Robe	Robin 300 Ledwash	2	21	304	Floor
Ledwash	Robe	Robin 300 Ledwash	2	21	325	Floor
Ledwash	Robe	Robin 300 Ledwash	2	21	346	Floor
		↓ 2x ↓				
Strobe	Martin	Atomic	Effects (4CH)	4	367	Floor
Strobe	Martin	Atomic	Effects (4CH)	4	371	Floor
		↓ 12x ↓				
Floorcan	DTS	1KW MFL	-	1	401	Floor



Legend

Symbol	Name	Count	Spares	Wattage	Lamp	Lens	Fixture Options
	PAR 64	72		1000	FFR - MFL		
	Robin 600E Wash	12		715	MSR GOLD 575/2 FastFit		Mode: 1
	Robin 600E Spot	12		715	MSR GOLD 575/2 FastFit		Mode: 1
	Atomic 3000	5		3600	XOP 7-OF		Channels: 4; Lamp: H Operation: Strobe
	PAR 64	13		250	ACL		
	ACL	11		250	ACL		
	4-Lite Mini Brute 2 cct	4		2600	FCX		